




ИНСТРУКЦИЯ ЗА МОНТАЖ

LED осветители SAMI

ПРОЧЕТИ ВНИМАТЕЛНО ПРЕДИ МОНТАЖА



(фиг. 2)



Model	Watt	Size (mm)			Rated voltage:
		L	W	H	U, V
SAMI20	20W	600	60	40	220-240 V
SAMI40	40W	1200	60	40	220-240 V

Характеристики:

- Алюминиев корпус;
- Цвят: Бял
- Степен на защита: IP 40;
- Осветителят е пригоден за монтиране върху нормално запалими повърхности
- Подходящ за закрепване на таван
- Мощности: 20W / 40W
- Работно напрежение: 220-240V, 50-60 Hz;
- Вграден LED driver,
- Тип LED: SMD EPISTAR, LED лента
- Температура на околната среда: до 45°C;
- Температура на корпуса на драйвера: до 75°C;
- Ниска консумация на енергия
- Ъгъл на светене: 180°
- Температура на светене: 4000 K;
- Светлинна ефективност: Ra>80;
- СССССС ОСССССССССССССССС 30000 ОССС
- Клас на защита от ел. ток: I (първи).

Приложение: подходящ за употреба в закрити пространства.

Монтаж:

С помощта на подходящи крепежи здраво закрепете осветителя върху тавана / стената.

- Издърпайте капачето от към гърба на лампата (фиг. 2) и свържете кабелите от люстер клемата към захранващата мрежа: кафяв към фаза L; син към неутрала N и жълто-зелен към заземяване. Ако дължината на кабела не е достатъчна, можете да направите електрическата връзка в кутията. Уверете се, че кабелът не докосва тялото и има достатъчна дължина, за да не се ограничават корекциите в

Мерки за безопасност:

- Електрическите и ремонтните работи винаги да се изпълняват от квалифициран персонал;
- Прекъснете захранването и изчакайте осветителя да се охлади, преди започване на каквато и да е работа;
- В случай на повреда, прекъснете захранването. Не се опитвайте да ремонтирате осветителя собственооръчно;

- Не гледайте директно в светодиодите отблизо или продължително време (повече от 5 минути). Това може да увреди ретината ви.

Предпазване на околната среда:



Извабените електрически продукти не трябва да се изхвърлят заедно с домакинските отпадъци. Моля предайте за рециклиране. Консултирайте се с вашите местни власти или търговеца. Фирмата е член на колективна система за рециклиране на ИУЕЕО на Трансинс Техно-рециклираща компания.


Забележка: Фирмата не носи отговорност при неизправности, причинени от неправилен монтаж.





INSTALLATION INSTRUCTION

LED Illuminator SAMI

READ CAREFULLY BEFORE INSTALLATION



(fig. 2)



Model	Watt	Size (mm)			Rated voltage:
		L	W	H	U, V
SAMI20	20W	600	60	40	220-240 V
SAMI40	40W	1200	60	40	220-240 V


Characteristics:

- Aluminium body
- Colour: White
- Protection degree: IP40
- The lighting body is adapted for installation on normally flammable surfaces
- Suitable for ceiling installation
- Capacities – 20W/40W
- Working electricity: 220- 240 V;50-60 Hz
- Inserted LED driver
- LED :SMD EPISTAR, LED strip
- Temperature of the environment: up to 45°C
- Temperature of the driver of the body: up to 75°C
- Low consumption of energy
- Beam angle -180°
- Temperature of lighting 4000K
- Lighting effectivity: Ra>80
- Exploitation term: 30000 hours
- Class of protection of electricity: I (first)

Attachment: suitable for usage in closed rooms and storages.

Installation:

Firmly attach the lighting body to the ceiling /wall helping with suitable fastenings.
- Pull out the lid of the back of the lamp (figure 2) and connect the cables from the luster terminal to the power supply :brown to phase L; blue to the neutral N and yellow -green to the earthing. If the length of the cable is not enough, you can make the electrical connection in the box. Please make assure that the cable does not touch the body and its length is enough in order not to limit the corrections in the positioning of the lighting body.



Safety measurements:

- The electrical activities must always be done by qualified staff;
- Turn off the power supply and wait until the lamp gets cold before starting to do whatever you have decided.
- In case of damage ,please turn off the power supply. Do not try to repair the lighting body by yourself.
- Do not look directly to the LED diods close to or for a longer time.(more than 5 minutes).This can damage your retina.**

Specifications:

- please kindly follow the chart.

Preserve of the environment :



The damaged electrical products must not be thrown away along with the household garbage. Please forward for recycling. Consult with your local authorities or your sales representative. The company is a member of a collective system of recycling of Electrical Equipment Out of Usage-Transins Technorecycling company.

Note: The company is not responsible for malfunctions, caused by inefficient mounting.